



Fluke Electrician Multimeter With Noncontact Voltage, 117, FLUKE-117, Grey & Yellow

Fluke 117 Digital Multimeter for Electricians with Non-Contact voltage

This Digital Multimeter includes integrated non-contact voltage detection to help get the job done faster. The Fluke 117 Digital Multimeter includes integrated non-contact voltage detection and Auto Volts and LoZ functions that help prevent false readings caused by ghost voltage. It is a compact True-RMS meter for demanding applications like commercial buildings, hospitals, and schools and helps get the job done faster.

SKU:

Price:

Stock: instock

Categories: [Fluke Product](#)

Product Description

Fluke 117 Digital Multimeter for Electricians with Non-Contact voltage

This Digital Multimeter includes integrated non-contact voltage detection to help get the job done faster. The Fluke 117 Digital Multimeter includes integrated non-contact voltage detection and Auto Volts and LoZ functions that help prevent false readings caused by ghost voltage. It is a compact True-RMS meter for demanding applications like commercial buildings, hospitals, and schools and helps get the job done faster. Users around the world have said their 117 digital multimeter is an investment in accuracy. The Fluke 117 provides Min/Max/Average readings and measures frequency and capacitance. Plus, its easy-to-use interface can save you time and enable you to move from job to job more quickly. The Fluke 110 Series has five true-rms digital multimeters, each for specific users. The compact instruments offer convenient one-handed operation and a backlit display with large, easy-to-read digits. Other useful features:

- Accurate, easy-to-use multimeter with integrated VoltAlert™ technology for non-contact voltage detection
- Features AutoVolt automatic AC/DC voltage selection
- Provides low input impedance to help prevent false readings due to ghost voltage
- Presents a large white LED backlight for working in poorly lit areas
- Features True RMS capabilities for accurate measurements on non-linear loads
- Measures 10 A (20 A overload for 30-seconds)
- Measures resistance, continuity, frequency, and capacitance

- Provides Min/Max/Average to record signal fluctuations
- Comes with an holster with probe holders for easy storage
- Features compact ergonomic design for one-handed operation
- Fits into optional ToolPak™ magnetic hanger for hands-free operation
- CAT III 600 V safety rated
- A large white LED backlight to improve measurement visibility in poorly lit areas
- VoltAlert™ technology for fast, go/no go non-contact voltage detection
- AutoVolt and low input impedance modes to provide faster, more accurate readings
- For commercial electricians, commercial and residential electrical work

Includes:

- 4 mm silicone test lead set
- Holster
- User manual

Key features

The 117 digital multimeter is a for electricians working in commercial and non-commercial premises that need non-contact voltage detection for faster and safer operations.

- Non-contact voltage detection
- AutoVolt automatic AC/DC voltage selection
- Prevent false readings caused by ghost voltage

Specifications: Fluke 117 Electricians Multimeter with Non-Contact voltage

Specifications

Maximum voltage between any terminal and earth ground	600 V	
Safety	IEC 61010-1: Pollution Degree 2 IEC 61010-2-033: CAT III 600V	
Fuse for A input	11 A, 1000 V FAST Fuse (Fluke PN 803293)	
Display	Digital: 6,000 counts, updates 4 per second	
Bar graph	33 segments, updates 32 per second	
Operating temperature	-10°C to +50°C	
Storage temperature	-40°C to +60°C	
Battery type	9 volt Alkaline, IEC 6LR61	
Battery life	400 hours typical, without backlight	
Accuracy Specifications		
DC millivolts	Range/resolution	600.0 mV / 0.1 mV
	Accuracy	±([% of reading] + [counts]): 0.5% + 2
DC volts	Range/resolution	6.000 V / 0.001 V 60.00 V / 0.01 V
		600.00 V / 0.1 V
	Accuracy	±([% of reading] + [counts]): 0.5% + 2

Auto volts	Range/resolution	600.0 V / 0.1 V
	Accuracy	2.0% + 3 (DC, 45 Hz to 500 Hz) 4.0% + 3 (500 Hz to 1 kHz)
AC millivolts ¹ True RMS	Range/resolution	600.0 mV / 0.1 mV
	Accuracy	1.0% + 3 (DC, 45 Hz to 500 Hz) 2.0% + 3 (500 Hz to 1 kHz)
AC volts ¹ True RMS	Range/resolution	6.000 V / 0.001 V 60.00 V / 0.01 V 600.0 V / 0.1 V
	Accuracy	1.0% + 3 (DC, 45 Hz to 500 Hz) 2.0% + 3 (500 Hz to 1 kHz)
Continuity	Range/resolution	600 ? / 1 ?
	Accuracy	Beeper on < 20 ?, off > 250 ? detects opens or shorts of 500 ?s or longer.
Ohms	Range/resolution	600.0 ? / 0.1 ? 6.000 k? / 0.001 k? 60.00 k? / 0.01 k? 600.0 k? / 0.1 k? 6.000 M? / 0.001 M?
	Accuracy	0.9% + 1
	Range/resolution	40.00 M? / 0.01 M?
	Accuracy	5% + 2
Diode test	Range/resolution	2.00 V / 0.001 V
	Accuracy	0.9% + 2
Capacitance	Range/resolution	1000 nF / 1 nF 10.00 ?F / 0.01 ?F 100.0 ?F / 0.1 ?F 9999 ?F / 1 ?F 100 ?F to 1000 ?F
	Accuracy	1.9% + 2
	Range/resolution	> 1000 ?F
	Accuracy	5% + 20%
Lo-Z capacitance	Range	1 nF to 500 ?F
	Accuracy	10% + 2 typical
AC amps True RMS (45 Hz to 500 Hz)	Range/resolution	6.000 A / 0.001 A 10.00 A / 0.01 A
	Accuracy	1.5% + 3 20 A continuous overload for 30 seconds max
DC amps	Range/resolution	6.000 A / 0.001 A 10.00 A / 0.01 A
	Accuracy	1.0% + 3 20 A continuous overload for 30 seconds max
Hz (V or A input) ²	Range/resolution	99.99 Hz / 0.01 Hz 999.9 Hz / 0.1 Hz 9.999 kHz / 0.001 Hz 50.00 kHz / 0.01 Hz
	Accuracy	0.1% + 2

1. All AC voltage ranges except Auto-V/LoZ are specified from 1% to 100% of range. Auto-V/LoZ is specified from 0.0 V. 2. Temperature uncertainty (accuracy) does not include the error of the thermocouple probe. 2. Frequency is AC coupled, 5 Hz to 50 kHz for AC voltage. Frequency is DC coupled, 45 Hz to 5 kHz for AC current. 2. Temperature Range/Resolution: -40°F to 752°F / 0.2°F.

Mechanical and General Specifications

Size	167 x 84 x 46 mm (6.57 x 3.31 x 1.82 in)
Weight	550 g
Warranty	3 years
